

Load selection charts

	Cat.Nos	Universal							
		Leading edge						Trailing edge	
		Incandescent lamp		Halogen lamp		ELV halogen with ferromagnetic transformer		ELV halogen with electronic transformer	
		110 V	230 V	110 V	230 V	110 V	230 V	110 V	230 V
Micropush switches	5740 04/54 5743 04/54	200 W	400 W	200 W	400 W	200 VA	400 VA	200 VA	400 VA
	5740 02/52 5743 02/52	500 W	1000 W	500 W	1000 W	250 VA	500 VA	250 VA	500 VA
	5740 03/53 5743 03/53	2 x 500 W	2 x 1000 W	2 x 500 W	2 x 1000 W	2 x 250 VA	2 x 500 VA	2 x 250 VA	2 x 500 VA
	5740 00/50 5743 00/50	3 x 500 W	3 x 1000 W	3 x 500 W	3 x 1000 W	3 x 250 VA	3 x 500 VA	3 x 250 VA	3 x 500 VA
	5740 01/51 5743 01/51	2 x 200 W	2 x 400 W	2 x 200 W	2 x 400 W	2 x 200 VA	2 x 400 VA	2 x 200 VA	2 x 400 VA
Sensitive switches	5720 51 5734 55 5725 51 5736 55	500 W	1000 W	500 W	1000 W	250 VA	500 VA	250 VA	500 VA
Dimmers	5740 06/56 5743 06/56	300 W	600 W	300 W	600 W	225 VA	450 VA	300 VA	600 VA
	5735 01 5737 01 5722 40 5727 40	500 W	1000 W	500 W	1000 W	500 VA	1000 VA	300 VA	600 VA
	5722 11 5727 11 5743 05/55	300 W	600 W	300 W	600 W	300 VA	600 VA		
	5722 39 5727 39 5743 19 5743 39	200 W	400 W	200 W	400 W	200 VA	400 VA	200 VA	400 VA
	5740 07/57 5743 07/57	2 x 200 W	2 x 400 W	2 x 200 W	2 x 400 W	2 x 200 VA	2 x 400 VA	2 x 200 VA	2 x 400 VA
	5722 41 5727 41	500 W	1000 W	500 W	1000 W	500 VA	1000 VA	500 VA	1000 VA
	5740 10/60	1100 W	2200 W	1100 W	2200 W	1100 VA	2200 VA	1100 VA	2200 VA

	Cat.Nos	Universal					
		Fluorescent tube		Compact fluorescent lamp		LED	
		110 V	230 V	110 V	230 V	110 V	230 V
Micropush switches	5740 02/52 5743 02/52	250 VA	500 VA	250 VA	500 VA	250 VA	500 VA
	5740 03/53 5743 03/53	2 x 250 VA	2 x 500 VA	2 x 250 VA	2 x 500 VA	2 x 250 VA	2 x 500 VA
	5740 00/50 5743 00/50	3 x 250 VA	3 x 500 VA	3 x 250 VA	3 x 500 VA	3 x 250 VA	3 x 500 VA
Sensitive switches	5720 51 5734 55 5725 51 5736 55	250 VA	500 VA	250 VA	500 VA	250 VA	500 VA
Dimmers	5722 39 5727 39 5743 19 5743 39	100 VA	200 VA	Dimmable 37 W (max. 10 lamps)	Dimmable 75 W (max. 10 lamps)	Dimmable 37 W (max. 10 lamps)	Dimmable 75 W (max. 10 lamps)

	Cat.Nos	Ballasts 0-10 V		Ballasts DALI		Reducer motor for shutters	
		110 V	230 V	110 V	230 V	110 V	230 V
Micropush switches	5740 02/52 5743 02/52					50 VA	100 VA
	5740 03/53 5743 03/53					2 x 50 VA	2 x 100 VA
	5740 00/50 5743 00/50					3 x 50 VA	3 x 100 VA
Sensitive switches	5720 51 5734 55 5725 51 5736 55					50 VA	100 VA
Dimmers	5722 38 5727 38 5743 18 5743 38	300 VA 40 mA	600 VA 40 mA				
	5740 10/60	1100 VA 50 mA	2200 VA 50 mA	60 ballast	60 ballast		